


AURA 1,2,3,4,5,9



TECHNICAL DATA

Light source	LED module Osmont L11B, L12B, L12C, L14B, L14C, L15B, L15C, L16B, L16C, L18C, L43C	incandescent lamp	fluorescent lamp
Chromacity temperature	3000K, 4000K	by source	by source
CRI	3000K Ra>80, 4000K Ra>80	by source	by source
Power source	Tridonic	-	Tridonic
Energy class	A++	by source	by source
Input voltage	230V		
IP	IP43		
Fixture	metal		
Color of fixture	white		
Shade	three layers glass with matt surface		
Shade attachment	with folding holders		
Mounting	wall, ceiling		
Applications	housing constructions (rooms, corridors), cultural premises		

VARIANTS

LED:

	Type	Input [W]	Luminous flux LED [lm]		Luminous flux of luminaire [lm]		Possibility				Warranty [yrs]*
			3000K	4000K	3000K	4000K	Sensor (HF)	DIM (DALI)	Corridor (DALI+HF)	2 circuits	
AURA 1	LED-1L11B07K2/040.000	8	970	1010	660	690	-	-	-	-	5
	LED-1L12C03K53/042.000	9	1080	1140	730	780	*	*	-	-	5
AURA 2	LED-1L12B07K53/042.000	11	1290	1350	880	920	*	*	-	-	5
	LED-1L18C03K53/042.000	15	2000	2110	1360	1430	*	*	-	-	5
AURA 3	LED-1L14C03K64/062.000	15	2000	2110	1360	1430	*	*	-	-	5
	LED-1L14B07K64/062.000	20	2590	2700	1760	1840	*	*	-	-	5
AURA 4	LED-1L15C07K75/072.000	21	2770	2920	2050	2160	*	*	-	-	5
	LED-1L15B07K75/072.000	29	3880	4050	2870	3000	*	*	-	-	5
AURA 5	LED-1L16C07K86/082.000	28	3690	3890	2550	2680	*	*	-	-	5
	LED-1L16B07K86/082.000	36	4850	5070	3350	3500	*	*	-	-	5
AURA 9	LED-2L43C07K98/084.000	37	5050	5330	3490	3680	-	*	-	-	5
	LED-2L43C10K98/084.000	56	7250	7640	5000	5270	-	*	-	-	5

LED emergency combined:

	Type	Input [W]	Luminous flux LED [lm]		Luminous flux of luminaire [lm]		Luminous flux LED in emergency mode		T [hrs]	Type of battery	Warranty [yrs]*
			3000K	4000K	3000K	4000K	[%]	[lm]			
AURA 1	LED-NZ1W/040.000	1	-	170	-	115	100	150	1	Ni-Mh (2,4V/2Ah)	5
AURA 2	LED-1L12C03K53/042/NK1W.000	9	1080	1140	730	780	13	150	3	Ni-Cd (3,6V/1,6Ah)	5
	LED-1L12B07K53/042/NK1W.000	11	1290	1350	880	920	11	150	3	Ni-Cd (3,6V/1,6Ah)	5
	LED-1L18C03K53/042/NK1W.000	15	2000	2110	1360	1430	7	150	3	Ni-Cd (3,6V/1,6Ah)	5
AURA 3	LED-1L14C03K64/062/NK1W.000	15	2000	2110	1360	1430	7	150	3	Ni-Cd (3,6V/1,6Ah)	5
	LED-1L14B07K64/062/NK1W.000	20	2590	2700	1760	1840	6	150	3	Ni-Cd (3,6V/1,6Ah)	5
AURA 4	LED-1L15C07K75/072/NK1W.000	21	2770	2920	2050	2160	5	150	3	Ni-Cd (3,6V/1,6Ah)	5
	LED-1L15B07K75/072/NK1W.000	29	3880	4050	2870	3000	4	150	3	Ni-Cd (3,6V/1,6Ah)	5
AURA 5	LED-1L16C07K86/082/NK1W.000	28	3690	3890	2550	2680	4	150	3	Ni-Cd (3,6V/1,6Ah)	5
	LED-1L16B07K86/082/NK1W.000	36	4850	5070	3350	3500	3	150	3	Ni-Cd (3,6V/1,6Ah)	5
AURA 9	LED-2L43C07K98/084/NK1W.000	37	5050	5330	3490	3680	3	150	3	Ni-Cd (3,6V/1,6Ah)	5
	LED-2L43C10K98/084/NK1W.000	56	7250	7640	5000	5270	2	150	3	Ni-Cd (3,6V/1,6Ah)	5

STANDARD:

	Type	Input [W]	Socket	Type of lamp	Possibility	
					Sensor (HF)	DIM (DALI)
AURA 1	IN-12K2/040	60	E27	-	-	-
	E-14K2/040	13	G24q1	TC-DEL	-	-
AURA 2	IN-12K52/042	100	E27	-	• (1x60W)	-
	IN-22K52/042	2x60	2xE27	-	-	-
	E-15K52/042	18	G24q2	TC-DEL	-	-
	E-16K52/042	26	G24q3	TC-DEL	-	-
AURA 3	IN-12K63/062	100	E27	-	• (1x75W)	-
	IN-22K63/062	2x75	2xE27	-	-	-
	E-16K63/062	26	G24q3	TC-DEL	-	-
	E-25K63/062	2x18	2xG24q2	TC-DEL	-	•
AURA 4	IN-22K74/072	2x75	2xE27	-	• (2x60W)	-
	E-26K74/072	2x26	2xG24q3	TC-DEL	-	•
	E-26K74/072 32W	2x32	2xGX24q3	TC-TEL	-	•
AURA 5	IN-32K86/082	3x60	3xE27	-	• (2x60W)	-
	E-27K86/082	2x36	2xG210	TC-F	-	-
	E-28K86/082	2x42	2xGX24q4	TC-TEL	-	-
AURA 9	IN-32K98/084	3x75	3xE27	-	-	-
	E-46K98/084	4x26	4xG24q3	TC-DEL	-	•
	E-46K98/084 32W	4x32	4xGX24q3	TC-TEL	-	-


STANDARD emergency combined:

	Type	Input [W]	Socket	Type of lamp	T [hrs]	Type of battery	Light flux in emergency mode [%]
AURA 1	NZ-7/040	7	2G7	TC-SEL	1	Ni-Cd 3,6V/1Ah	22
AURA 2	NZ-13/042	13	G24q1	TC-DEL	1	Ni-Cd 3,6V/1,5Ah	16
	NK-E-13/042	13	G24q1	TC-DEL	1	Ni-Cd 3,6V/1,5Ah	16
	NK-E-18/042	18	G24q2	TC-DEL	1	Ni-Cd 3,6V/1,5Ah	14
AURA 3	NK-E-26/062	26	G24q3	TC-DEL	1	Ni-Cd 3,6V/1,5Ah	10
AURA 4	NKC-226/13/072	2x26	2xG24q3	TC-DEL	1	Ni-Cd 3,6V/1,5Ah	8
AURA 5	NKC-232/16/082	2x32	2xGX24q3	TC-TEL	1	2x Ni-Cd 3,6V/1,6Ah	9
AURA 9	NKC-242/16/084	2x42	2xGX24q4	TC-TEL	1	2x Ni-Cd 3,6V/1,6Ah	6,5

.000 – 3000K or 4000K
* – warranty on LED modules and power sources

DIMENSIONS

DIMENSIONS OF LUMINAIRE [mm]:



	ØA1	A2
AURA 1	220	110
AURA 2	280	120
AURA 3	350	120
AURA 4	420	125
AURA 5	490	130
AURA 9	590	140

MOUNTING DIMENSIONS [mm]:

AURA 1				
	IN-..., E-...	NZ-...	LED-...	LED-NZ1W
AURA 2				
	IN-..., E-..., NZ-..., NK-E-...		LED-...	

AURA 3	Technical drawing of a circular panel (AURA 3) with a diameter of $\varnothing 275$. The panel features four mounting points (indicated by diamond symbols) and two central mounting points (indicated by circles with a cross). The dimensions are as follows: the distance between the top and bottom mounting points is 164; the distance between the left and right mounting points is 164; the distance from the center to the top mounting point is 82; the distance from the center to the bottom mounting point is 105; the distance from the center to the left mounting point is 82; and the distance from the center to the right mounting point is 20.
AURA 4	Technical drawing of a circular panel (AURA 4) with a diameter of $\varnothing 325$. The panel features four mounting points (indicated by diamond symbols) and two central mounting points (indicated by circles with a cross). The dimensions are as follows: the distance between the top and bottom mounting points is 190; the distance between the left and right mounting points is 190; the distance from the center to the top mounting point is 95; the distance from the center to the bottom mounting point is 115; the distance from the center to the left mounting point is 95; and the distance from the center to the right mounting point is 20.
AURA 5	Technical drawing of a circular panel (AURA 5) with a diameter of $\varnothing 375$. The panel features four mounting points (indicated by diamond symbols) and two central mounting points (indicated by circles with a cross). The dimensions are as follows: the distance between the top and bottom mounting points is 221; the distance between the left and right mounting points is 221; the distance from the center to the top mounting point is 110; the distance from the center to the bottom mounting point is 140; the distance from the center to the left mounting point is 110; and the distance from the center to the right mounting point is 20.
AURA 9	Technical drawing of a circular panel (AURA 9) with a diameter of $\varnothing 465$. The panel features four mounting points (indicated by diamond symbols) and two central mounting points (indicated by circles with a cross). The dimensions are as follows: the distance between the top and bottom mounting points is 280; the distance between the left and right mounting points is 280; the distance from the center to the top mounting point is 140; the distance from the center to the bottom mounting point is 183; the distance from the center to the left mounting point is 140; and the distance from the center to the right mounting point is 10.